



**HAL**  
open science

# Equivalent Conditions for the Synchronization of Identical Linear Systems over Arbitrary Interconnections

Nicola Zaupa, Giulia Giordano, Isabelle Queinnec, Sophie Tarbouriech, Luca  
Zaccarian

► **To cite this version:**

Nicola Zaupa, Giulia Giordano, Isabelle Queinnec, Sophie Tarbouriech, Luca Zaccarian. Equivalent Conditions for the Synchronization of Identical Linear Systems over Arbitrary Interconnections. 2023. hal-04359774

**HAL Id: hal-04359774**

**<https://laas.hal.science/hal-04359774>**

Preprint submitted on 21 Dec 2023

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



Distributed under a Creative Commons Attribution - NonCommercial - NoDerivatives 4.0  
International License

# Equivalent Conditions for the Synchronization of Identical Linear Systems over Arbitrary Interconnections <sup>\*</sup>

Nicola Zaupa<sup>a,\*</sup>, Giulia Giordano<sup>b</sup>, Isabelle Queinnec<sup>a</sup>, Sophie Tarbouriech<sup>a</sup>, Luca Zaccarian<sup>a,b</sup>

<sup>a</sup>LAAS – CNRS, Université de Toulouse, CNRS, Toulouse, France.

<sup>b</sup>Dipartimento di Ingegneria Industriale, Università di Trento, Trento, Italy.

---

## Abstract

We propose necessary and sufficient conditions for the synchronization of  $N$  identical single-input-single-output (SISO) systems, connected through a directed graph. We consider both the continuous-time and the discrete-time case, and we provide conditions that do not require any assumption on the graph and ensure the uniform global exponential stability of the closed attractor that corresponds to the synchronization set, with guaranteed convergence rate.

*Keywords:* Synchronization, uniform global exponential stability, multi-agents system, identical agents, LTI

---

## 1. Introduction

The problems of consensus and synchronization of multi-agent systems (Fagnani and Frasca, 2017) have received growing interest, due to the variety of applications in many different areas, including: cooperative control of unmanned aerial vehicles, formation control of mobile robots and communication in sensor networks (Fax and Murray, 2004; Jadbabaie et al., 2003; Ren et al., 2007), quality-fair delivery of media contents (Dal Col et al., 2017), power networks (Dörfler et al., 2013), biological systems (Scardovi et al., 2010), and opinion dynamics (Anderson and Ye, 2019). Specifically, *consensus* refers to agents coming to a global agreement on a state value, thanks to the exchange of information modeled by some communication graph; mild assumptions on the graph connectivity allow to uniformly exponentially reach consensus (Jadbabaie et al., 2003; Olfati-Saber and Murray, 2004; Olfati-Saber et al., 2007; Moreau, 2005; Ren and Beard, 2008; Wieland et al., 2008; Seo et al., 2009). Conversely, *synchronization* refers to agents moving toward a common trajectory in the configuration space (Hale, 1997; Pecora and Carroll, 1998; Slotine and Wang, 2005; Scardovi and Sepulchre, 2009; Carli et al., 2011; Sepulchre, 2011; Andrieu et al., 2018; Dal Col et al., 2018, 2019). Consensus and synchronization problems have been widely investigated for agents modelled by identical linear time-invariant (LTI) systems, with many subsequent extensions to switching network topologies (Olfati-Saber and Murray, 2004; Xiao and Wang, 2007; Su and Huang, 2012), heterogeneous and nonlinear systems (Khong et al., 2016; Panteley and Loria, 2017; Adhikari et al., 2021), output synchronization (Zhu et al., 2016; Isidori, 2017), and hybrid systems (Mayhew et al., 2012; Teel and Poveda, 2015; Cristofaro and Mattioni, 2022).

Figure 1 represents the distributed feedback system addressed in this work, where  $N$  identical SISO dynamical systems of arbitrary order, with state  $x_i \in \mathbb{R}^n$  evolving as

$$\begin{aligned} \dot{x}_i/x_i^+ &= Ax_i + Bu_i \\ y_i &= Cx_i + du_i \end{aligned} \quad i = 1, \dots, N \quad (1)$$

---

<sup>\*</sup>This work was supported in part by the MUR under PRIN grant DOCEAT [grant number 2020RTWES4].

<sup>\*</sup>Corresponding author.

Email addresses: nzaupa@laas.fr (Nicola Zaupa), giulia.giordano@unitn.it (Giulia Giordano), queinnec@laas.fr (Isabelle Queinnec), tarbour@laas.fr (Sophie Tarbouriech), zaccarian@laas.fr (Luca Zaccarian)




Figure 1: Block diagram of the closed-loop system.

and with scalar inputs  $u_i \in \mathbb{R}$  and outputs  $y_i \in \mathbb{R}$ , are interconnected through a directed graph  $\mathcal{G}$  with Laplacian  $L \in \mathbb{R}^{N \times N}$  as follows:

$$u = -Ly = -L((I_N \otimes C)x + du), \quad (2)$$

where  $u = [u_1 \dots u_N]^\top \in \mathbb{R}^N$ ,  $y = [y_1 \dots y_N]^\top \in \mathbb{R}^N$  and  $x := [x_1^\top \dots x_N^\top]^\top \in \mathbb{R}^{Nn}$ , are the aggregate input, output and state vectors, respectively, and  $\otimes$  denotes the Kronecker product.

Due to linearity, a range of equivalent conditions for synchronization can be stated and may lead to powerful numerical tools for distributed controllers tuning. Despite the extensive amount of work in the field, one cannot find a *general* theorem clearly stating the equivalence of these conditions for identical LTI systems of *arbitrary* order, connected through an *arbitrary* graph topology. Here, we provide this result by introducing a list of necessary and sufficient conditions for uniform global exponential synchronization with guaranteed convergence rate both in the continuous-time and in the discrete-time case. For the sake of generality, we also allow for the presence of a direct input-output link  $d \in \mathbb{R}$  in (1). With  $d \neq 0$ , the implicit equation (2) can be uniquely solved as

$$u = -(L_d \otimes C)x := -((I_N + dL)^{-1}L \otimes C)x \quad (3)$$

if and only if (linear) well-posedness holds, namely matrix  $I_N + dL$  is invertible or, equivalently,  $-d^{-1}$  is not an eigenvalue of  $L$ . Clearly, when  $d = 0$  we retrieve the classical case  $L_d := (I_N + dL)^{-1}L = L$ , but our results also characterize the general case with a distributed algebraic loop. Overall, the linear distributed interconnection (1), (2) can be written as

$$\dot{x}/x^+ = (I_N \otimes A)x - (L_d \otimes BC)x. \quad (4)$$

Our main contribution consists in providing a list of necessary and sufficient conditions for the uniform global exponential stability of the synchronization set with convergence rate guarantees. We consider the synchronization set, i.e., the (unbounded) set where all pairwise states coincide. These conditions comprise (a) Hurwitz/Schur properties of complex-valued matrices induced by the eigenvalues of  $L_d$ , (b) equivalent Hurwitz/Schur properties of suitable real-valued matrices, (c) existence of positive-definite solutions to certain Lyapunov inequalities, (d) existence of a strict quadratic Lyapunov function (establishing a quadratic converse Lyapunov theorem), and (e) synchronization of all solutions towards a specific initial value problem.

Proving equivalence of the above properties is a contribution per se, as typically one finds only parts of these equivalences in the literature, possibly with different assumptions on the Laplacian  $L$ . Conditions of the same form as (a) for formation stability were given in (Fax and Murray, 2004, Theorem 3) and the uniform global exponential stability condition was exploited in (Xia and Scardovi, 2014, Theorem 1) and (Seo et al., 2009, Theorem 1). The condition related to the initial value problem (e) was given in (Scardovi and Sepulchre, 2009). Moreover, a list of similar discrete-time statements was given under an undirected graph assumption in (Dal Col et al., 2017, Theorem 1)

The presented necessary and sufficient conditions allow us to parametrize all possible stabilizers and possibly select the *best* one from a certain performance view-point. For example, analogous conditions have been used in the recent work (Zaupa et al., 2023) for the design of a simultaneous stabilizing static state-feedback controller in comparison with existing approaches where Riccati-based designs are used to show the existence of a stabilizer. Our proposed conditions can be used to extend the LMI-based  $H_\infty$  results in (Dal Col, 2016), as well as the LMI-based saturated feedback design in (Dal Col et al., 2019), to also deal with undirected graphs. More in general, while existence results for global simultaneous stabilizers are already available from (Isidori, 2017; Saberi et al., 2022), our conditions become relevant when solving a multi-objective control (or observer) design problem.

The paper is structured as follows. Section 2 presents basic definitions along with the main theorem, whose proof is provided in Section 3.

**Notation.**  $\mathbb{R}$  ( $\mathbb{R}_{\geq 0}$ ),  $\mathbb{C}$  and  $\mathbb{N}$  denote respectively the sets of real (non-negative), complex and natural numbers. We denote with  $j$  the imaginary unit and with  $\mathbf{1}_N \in \mathbb{R}^N$  ( $\mathbf{0}_N \in \mathbb{R}^N$ ) the  $N$ -dimensional (column) vector having all 1 entries (0 entries);  $\text{diag}(A_1, \dots, A_N)$  indicates the block diagonal matrix whose diagonal blocks are the square matrices  $A_1, \dots, A_N$ . Given a complex number  $\lambda = a + jb$ ,  $\text{Re}(\lambda) = a$  denotes its real part,  $\text{Im}(\lambda) = b$  its imaginary part,  $\lambda^* = a - jb$  its complex conjugate. Given a complex matrix  $A \in \mathbb{C}^{n \times m}$ ,  $A^*$  denotes its conjugate transpose. A square matrix  $A \in \mathbb{C}^{n \times n}$  is Hurwitz when all its eigenvalues have strictly negative real part; it is Schur when all its eigenvalues have modulus strictly less than 1; it is Hermitian if  $A = A^*$ , namely  $\text{Re}(A)$  is symmetric ( $\text{Re}(A) = \text{Re}(A)^T$ ) and  $\text{Im}(A)$  is skew-symmetric ( $\text{Im}(A) = -\text{Im}(A)^T$ ). A Hermitian matrix  $A$  has real eigenvalues and is positive semi-definite,  $A \geq 0$  (resp. positive definite,  $A \succ 0$ ), when its eigenvalues are all non-negative (resp. positive). We denote with  $\sigma(A)$  the spectrum of a square matrix  $A$ , and we call *dominant* the eigenvalue having the largest real part. Eigenpairs for which  $Av = \lambda v$  are denoted as  $(\lambda, v)$ . We denote the Euclidean distance of a point  $x$  from a set  $\mathcal{X}$  as  $|x|_{\mathcal{X}} := \inf_{y \in \mathcal{X}} |x - y|$ . The topology of a directed graph  $\mathcal{G}$  with  $N \in \mathbb{N}$  nodes is characterized by the weighted adjacency matrix  $\mathcal{W} \in \mathbb{R}^{N \times N}$  whose entry  $\mathcal{W}_{ij} \geq 0$  denotes the weight of the edge pointing from node  $j$  to node  $i$ . Defining the diagonal matrix  $D := \text{diag}(\mathcal{W} \mathbf{1}_N)$ , we can introduce the Laplacian matrix  $L := D - \mathcal{W}$  associated with the graph  $\mathcal{G}$ .

## 2. Equivalent conditions to $\alpha$ -synchronization

To establish synchronization among systems (1), interconnected via (2), as represented in Figure 1, we first introduce the synchronization set, or *attractor*,

$$\mathcal{A} := \{x : x_i - x_j = 0, \forall i, j \in \{1, \dots, N\}\} \quad (5)$$

along with the definitions of exponential stability and synchronization for the continuous-time and the discrete-time case, for a given convergence rate  $\alpha$ .

**Definition 1** ( $\alpha$ -UGES). *The attractor  $\mathcal{A}$  in (5) is  $\alpha$ -UGES (uniformly globally exponentially stable with rate  $\alpha > 0$ ) for system (1), (2) if there exists  $M > 0$  such that any solution  $t \mapsto x(t)$  satisfies*

$$|x(t)|_{\mathcal{A}} \leq M e^{-\alpha t} |x(0)|_{\mathcal{A}}, \quad \forall t \in \mathbb{R}_{\geq 0} \quad (6a)$$

$$\left(\text{resp. } |x(t)|_{\mathcal{A}} \leq M \alpha^t |x(0)|_{\mathcal{A}}, \quad \forall t \in \mathbb{N}\right). \quad (6b)$$

**Remark 1.** The definition above considers exponential stability of the attractor, which coincides with its asymptotic stability due to the linear and homogeneous dynamics of the system.  $\lrcorner$

**Definition 2** ( $\alpha$ -synchronization). *For the continuous-time (respectively discrete-time) linear system (1), (2),  $\alpha$ -synchronization holds if there exist  $M > 0$  and rate  $\alpha > 0$  (resp.  $\alpha \in (0, 1)$ ) such that, for any initial condition, every sub-system satisfies*

$$|x_i(t) - \tilde{x}_o(t)| \leq M e^{-\alpha t} \sum_{i=1}^N |x_i(0) - \tilde{x}_o(0)|, \quad \forall t \in \mathbb{R}_{\geq 0} \quad (7a)$$

$$\left(\text{resp. } |x_i(t) - \tilde{x}_o(t)| \leq M \alpha^t \sum_{i=1}^N |x_i(0) - \tilde{x}_o(0)|, \quad \forall t \in \mathbb{N}\right), \quad (7b)$$

$i = 1, \dots, N$ , for a suitable target trajectory  $\tilde{x}_o$ , depending on the initial conditions.

Before stating our main result, we note that, trivially, all the zero eigenvalues of  $L$  are also zero eigenvalues of  $L_d = (I_N + dL)^{-1}L$ . Then we denote by  $0 = \lambda_0, \lambda_1, \dots, \lambda_\nu$  the eigenvalues of  $L_d$ , where the complex conjugate pairs are only counted once (so that  $\nu := N - 1 - n_c$ , with  $n_c$  being the number of complex conjugate pairs).

Given an assigned convergence rate  $\alpha^* \geq 0$  of the solutions towards the attractor  $\mathcal{A}$ , we state a list of necessary and sufficient conditions for (continuous- or discrete-time)  $\alpha^*$ -exponential synchronization of (1), (2).

**Theorem 1.** Consider the continuous-time (resp. discrete-time) system in (1), (2), the attractor  $\mathcal{A}$  in (5) and the parameter  $\alpha^* \geq 0$  (resp.  $\alpha^* \in (0, 1]$ ). The following statements are equivalent:

(i). [Complex condition] The spectral abscissa (resp. spectral radius) of the complex-valued matrices<sup>1</sup>

$$A_k := A - \lambda_k BC, \quad k = 1, \dots, \nu, \quad (8)$$

is smaller than  $-\alpha^*$  (resp.  $\alpha^*$ ).

(ii). [Real condition] The spectral abscissa (resp. spectral radius) of the real-valued matrices

$$A_{e,k} := \begin{bmatrix} A - \operatorname{Re}(\lambda_k)BC & \operatorname{Im}(\lambda_k)BC \\ -\operatorname{Im}(\lambda_k)BC & A - \operatorname{Re}(\lambda_k)BC \end{bmatrix}, \quad k = 1, \dots, \nu, \quad (9)$$

is smaller than  $-\alpha^*$  (resp.  $\alpha^*$ ).

(iii). [Lyapunov inequality] For each  $k = 1, \dots, \nu$ , there exist real-valued matrices  $P_k = P_k^\top \succ 0$  and  $\Pi_k^\top = -\Pi_k$  such that one of the following identities holds:

$$(P_k + j\Pi_k)A_k + A_k^*(P_k + j\Pi_k) \prec -2\alpha^*(P_k + j\Pi_k) \quad (10a)$$

$$\left( \text{resp. } A_k^*(P_k + j\Pi_k)A_k \prec (\alpha^*)^2(P_k + j\Pi_k) \right), \quad (10b)$$

or

$$\begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} A_{e,k} + A_{e,k}^\top \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} \prec -2\alpha^* \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} \quad (11a)$$

$$\left( \text{resp. } A_{e,k}^\top \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} A_{e,k} \prec (\alpha^*)^2 \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} \right). \quad (11b)$$

(iv). [Lyapunov function] There exist  $\alpha > \alpha^*$  (resp.  $0 < \alpha < \alpha^*$ ), positive constants  $c_1$ ,  $c_2$  and  $c_3$ , and a strict quadratic Lyapunov function  $V(x)$  satisfying:

$$c_1 |x|_{\mathcal{A}}^2 \leq V(x) \leq c_2 |x|_{\mathcal{A}}^2, \quad (12a)$$

$$\dot{V}(x) \leq -2\alpha V(x) \quad (12b)$$

$$\left( \text{resp. } V(x^+) \leq \alpha^2 V(x) \right). \quad (12c)$$

(v). [UGES] There exists  $\alpha > \alpha^*$  (resp.  $0 < \alpha < \alpha^*$ ) such that the closed attractor  $\mathcal{A}$  in (5) is  $\alpha$ -UGES for the closed loop (1), (2).

(vi). [IVP] There exists  $\alpha > \alpha^*$  (resp.  $0 < \alpha < \alpha^*$ ) such that, for the closed loop (1), (2), the sub-states  $x_i$  uniformly globally  $\alpha$ -exponentially synchronize to the unique solution of the following initial value problem:

$$\dot{\tilde{x}}_o / \tilde{x}_o^+ = A\tilde{x}_o, \quad \tilde{x}_o(0) = \frac{1}{p^\top \mathbf{1}_N} \sum_{k=1}^N p_k x_k(0), \quad (13)$$

where  $p := [p_1 \dots p_N]^\top \in \mathbb{R}^N$  is a left eigenvector corresponding to the zero eigenvalue of  $L$ .

**Remark 2.** Referring to item (vi) above, the  $k$ -th entry of the left eigenvector  $p$ , associated with the zero eigenvalue of the Laplacian  $L$ , can be seen as a measure of the *centrality* of node  $k$ , which weighs its initial state in the linear combination  $\tilde{x}_o(0)$  in (13); a strong analogy can be observed with the Bonacich centrality (Bonacich, 1987), which is the left eigenvector associated with the 1 eigenvalue of the normalized adjacency matrix.  $\lrcorner$

<sup>1</sup>With complex conjugate pairs  $\lambda_k, \lambda_k^*$ , it is enough to check condition (8) for one of the two eigenvalues. Indeed, if  $(A - \lambda_k BC)(v + jw) = \mu(v + jw)$ , then by taking the conjugate we get  $(A - \lambda_k^* BC)(v - jw) = \mu^*(v - jw)$ , where  $\mu$  and its conjugate  $\mu^*$  have the same real part and the same modulus.

**Remark 3.** Theorem 1 holds also for weakly-connected or even disconnected graph. In this situation, the algebraic multiplicity of the zero eigenvalue of  $L$  is greater than one and therefore we have the trivial condition that matrix  $A$  has to be Hurwitz/Schur. This is a reasonable conclusion: for a disconnected network, the only possible common equilibrium without information exchange is the origin. Moreover, referring to item (vi), in this case the vector  $p$  is not uniquely determined (up to rescaling) since there exist as many linearly independent eigenvectors as the geometric multiplicity of the zero eigenvalue. In fact, any such selection of  $p$  is a valid one for item (vi) because, with disconnected networks, all the equivalent items of the theorem are true if and only if the solution of (13) converges to zero (a trivial synchronized motion).  $\lrcorner$

In the special case where  $\alpha^* = 0$  (resp.  $\alpha^* = 1$ ) and  $d = 0$ , matrix  $L_d$  becomes the Laplacian  $L$  of the graph, and the results in Theorem 1 can be stated in a simplified (and widely studied) setting, as clarified in the next corollary.

**Corollary 1.** Consider the continuous-time (resp. discrete-time) system (1), (2) with  $d = 0$ , so that  $0 = \lambda_0, \lambda_1, \dots, \lambda_\nu$  are the eigenvalues of  $L$ . The following statements are equivalent

- (i). [Complex condition] The complex-valued matrices (8) are Hurwitz (resp. are Schur).
- (ii). [Real condition] The real-valued matrices (9) are Hurwitz (resp. are Schur).
- (iii). [Lyapunov inequality] For each  $k = 1, \dots, \nu$ , there exist real-valued matrices  $P_k = P_k^\top \succ 0$  and  $\Pi_k^\top = -\Pi_k$  such that one of the following identities holds:

$$(P_k + J\Pi_k)A_k + A_k^*(P_k + J\Pi_k) \prec 0 \quad (\text{resp. } A_k^*(P_k + J\Pi_k)A_k \prec 0),$$

or

$$\begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} A_{e,k} + A_{e,k}^\top \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} \prec 0 \quad \left( \text{resp. } A_{e,k}^\top \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} A_{e,k} \prec 0 \right).$$

- (iv). [Lyapunov function] There exist positive constants  $c_1, c_2$  and  $c_3$  and a strict quadratic Lyapunov function  $V$  satisfying (12a) and  $\dot{V}(x) \leq -c_3 V(x)$  (resp.  $V(x^+) \leq (1 - c_3)V(x)$ ) for all  $x \in \mathbb{R}^{Nn}$ .
- (v). [UGES] The closed attractor  $\mathcal{A}$  in (5) is uniformly globally exponentially stable.
- (vi). [IVP] The closed loop (1), (2) is such that the sub-states  $x_i$  uniformly globally exponentially synchronize to the unique solution of the initial value problem (13).

**Remark 4.** In the continuous-time case, following (Hara et al., 2014, Lemma 1), comparing the dynamic matrix  $\mathbf{A} := (I_N \otimes A) - (L \otimes BC)$  arising from (4) with (Hara et al., 2014, equation (4)), we may give an additional frequency-domain condition, equivalent to the above items, expressed in terms of a coprime factorization  $\frac{\bar{n}(s)}{\bar{d}(s)} = C(sI - A)^{-1}B$  of dynamics (1) as follows:

- (vii). [Frequency domain]  $\sigma(L) \subset \Lambda := \{\lambda \in \mathbb{C} : \bar{d}(s) + \lambda \bar{n}(s) \text{ is Hurwitz}\}$ .  $\lrcorner$

### 3. Proof of the main theorem

#### 3.1. A few technical lemmas

Before proving Theorem 1, we state some preliminary facts useful for the proof. We prove the following standard result to highlight that no assumptions on the graph  $\mathcal{G}$  are needed.

**Lemma 1.** Given any (directed) graph  $\mathcal{G}$  and its Laplacian  $L = D - \mathcal{W}$ , the eigenvalues of  $M := -L$  have non-positive real part and the dominant eigenvalue of  $M$  is  $\mu_0 = 0$ . It is associated with a right eigenvector  $\mathbf{1}_N$  and a left eigenvector  $p \in \mathbb{R}^N$  that can be selected non-negative.

*Proof.* Since  $\mathcal{W}$  has non-negative elements by construction and  $D$  is diagonal,  $M = \mathcal{W} - D$  is a Metzler matrix (i.e., its off-diagonal entries are non-negative). Hence, as a consequence of Perron-Frobenius theory, the dominant eigenvalue  $\mu_0$  of  $M$  is real and associated with left and right eigenvectors having non-negative elements (Luenberger, 1979, Chapter 6.5, Theorem 1). In view of Gershgorin's Circle Theorem (Horn and Johnson, 2012, Chapter 6.1), the eigenvalues of  $M$  lie in the union of the  $N$  disks centered at  $-D_{ii}$  and with radius  $\sum_{j=1}^N \mathcal{W}_{ij} = D_{ii}$ ,  $i = 1, \dots, N$ , which are all included in the left half plane and tangent to the imaginary axis at zero. Therefore, all the eigenvalues have non-positive real part and the only possible eigenvalue whose real part is not strictly negative is zero.  $M$  is singular, because  $M\mathbf{1}_N = \mathbf{0}_N$ . Then,  $\mu_0 = 0$  is the dominant eigenvalue and we can select  $\mathbf{1}_N$  as a right eigenvector and a vector with non-negative elements as a left eigenvector.  $\square$

We will rely on the following lemma for the decomposition of the closed-loop dynamics.

**Lemma 2.** Consider the matrix  $L_d \in \mathbb{R}^{N \times N}$  defined as  $L_d = (I_N + dL)^{-1}L$ , where  $L \in \mathbb{R}^{N \times N}$  is the Laplacian of a directed graph  $\mathcal{G}$  and  $d \in \mathbb{R}$  is such that  $(I_N + dL)$  is invertible. There exists an orthogonal matrix  $T$ , whose first column is  $\frac{1}{\sqrt{N}}\mathbf{1}_N$ , that transforms  $L_d$  into a block upper triangular matrix:

$$\bar{L}_d := T^\top L_d T = \begin{bmatrix} \lambda_0 & * & \dots & * \\ 0 & \Lambda_1 & \dots & * \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & \Lambda_\nu \end{bmatrix} = \begin{bmatrix} 0 & * & \dots & * \\ 0 & \Lambda_1 & \dots & * \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & \Lambda_\nu \end{bmatrix}, \quad (14)$$

where blocks  $\Lambda_i$ ,  $i = 1, \dots, \nu$ , are either scalar (corresponding to real eigenvalues of  $L_d$ ) or 2-by-2 matrices (corresponding to complex conjugate eigenvalue pairs of  $L_d$ ).

*Proof.* First, from (Horn and Johnson, 2012, Theorem 2.3.4, item (b)) it follows that there exists an orthogonal  $T$  such that  $L_d$  can be decomposed as in (14) with no particular structure for  $\Lambda_i$ . Second,  $L$  and  $L_d$  share the same eigenspace associated with the zero eigenvalue. To show this, let us consider the eigenpair  $(0, w)$  for  $L$ , such that  $Lw = 0$ . Then, since  $L_d = (I_N + dL)^{-1}L$ , we have that  $L_d w = (I_N + dL)^{-1}Lw = 0$ . This means that  $(0, w)$  is also an eigenpair for  $L_d$  and therefore the zero eigenvalue has the same algebraic and geometric multiplicity for both  $L$  and  $L_d$ . Third, from (Agaev and Chebotarev, 2005, Theorem 4) and (Caughman and Veerman, 2006, Corollary 4.2), the zero eigenvalue of  $L$  is semisimple (i.e., its algebraic and geometric multiplicities coincide), which holds also for  $L_d$  since they share the same eigenspace. Finally, in order to have the first entry of  $\bar{L}_d$  equal to zero and  $T$  orthogonal, the first column of  $T$  must be equal to  $\frac{1}{\sqrt{N}}\mathbf{1}_N$  so that  $\left(\frac{1}{\sqrt{N}}\mathbf{1}_N\right)^\top \left(\frac{1}{\sqrt{N}}\mathbf{1}_N\right) = 1$ .  $\square$

We will also use the following results, which trivially follow from (Stykel, 2002) for the particular case  $E = I$ , that guarantee necessary and sufficient conditions for a complex matrix to be Hurwitz or Schur. In particular, for the continuous-time case we consider (Stykel, 2002, Theorem 2.3).

**Lemma 3.** A matrix  $S \in \mathbb{C}^{n \times n}$  is Hurwitz if and only if, for each positive definite  $Q \in \mathbb{C}^{n \times n}$ ,  $Q^* = Q$ , there exists a positive definite  $H \in \mathbb{C}^{n \times n}$ , with  $H^* = H$ , such that  $S^*H + HS = -Q$ .

For the discrete-time case we consider (Stykel, 2002, Theorem 3.2), which is a generalization of the results in (Wimmer, 1973, Theorem 7).

**Lemma 4.** A matrix  $S \in \mathbb{C}^{n \times n}$  is Schur if and only if, for each positive definite  $Q \in \mathbb{C}^{n \times n}$ ,  $Q^* = Q$ , there exists a positive definite  $H \in \mathbb{C}^{n \times n}$ , with  $H^* = H$ , such that  $S^*HS - H = -Q$ .

For the continuous-time case, the proof combines the stability results in (Fax and Murray, 2004) with the output feedback coupling approach of (Scardovi and Sepulchre, 2009). Parts of the result can be found in the literature, possibly with different assumptions on the Laplacian  $L$ . For example, necessary and sufficient conditions of the form (i) for formation stability were given in (Fax and Murray, 2004, Theorem 3); implication (i)  $\implies$  (v) was established in an equivalent formulation in (Xia and Scardovi, 2014, Theorem 1) and (Seo et al., 2009, Theorem 1) for the convergence part. In (Wieland et al., 2011), the equivalence (i)  $\iff$  (vi) was proven. For the discrete-time case, in (Dal Col et al., 2017, Theorem 1) a similar statement is given under an undirected graph assumption.

### 3.2. Proof of Theorem 1

The proof is structured as follows: we first prove the equivalence among items (i), (ii) and (iii). Then we prove (iii)  $\implies$  (iv), followed by (iv)  $\implies$  (v), (v)  $\implies$  (vi), and finally (vi)  $\implies$  (ii).

**Proof of (i)  $\iff$  (ii).** Given the complex-valued matrix  $A_k = M_k + jN_k \in \mathbb{C}^{n \times n}$ , where  $M_k, N_k \in \mathbb{R}^{n \times n}$ , following (Bernstein, 2005, Fact 2.17.3) we can write

$$A_{e,k} = \begin{bmatrix} M_k & N_k \\ -N_k & M_k \end{bmatrix} = \begin{bmatrix} I_n & 0 \\ jI_n & I_n \end{bmatrix} \begin{bmatrix} M_k + jN_k & N_k \\ 0 & M_k - jN_k \end{bmatrix} \begin{bmatrix} I_n & 0 \\ -jI_n & I_n \end{bmatrix}, \quad (15)$$

from which it follows that  $\sigma(A_{e,k}) = \sigma(A_k) \cup \sigma(A_k^*)$ . The implication (i)  $\iff$  (ii) directly follows from the fact that (15) implies  $\sigma(A_k) \subseteq \sigma(A_{e,k})$ . To show (i)  $\implies$  (ii), note that  $\sigma(A_k^*) = (\sigma(A_k))^*$ , which means that the spectral abscissa (resp. the spectral radius) of  $A_k$  and  $A_k^*$  are the same. As a consequence, also the union of their spectrum preserves the same properties, i.e.  $A_{e,k}$  has the same spectral abscissa (resp. the same spectral radius) as  $A_k$ , thus concluding the proof of (i)  $\iff$  (ii).

**Proof of (i)  $\iff$  (iii).** Statement (i) is equivalent to imposing that  $A_k + \alpha^* I$  is Hurwitz (resp.  $\frac{1}{\alpha^*} A_k$  is Schur). Therefore, for the continuous-time case, in view of Lemma 3, Hurwitz stability of  $A_k + \alpha^* I$  is equivalent to  $A_k^* H_k + H_k A_k < -2\alpha^* H_k$  for a positive definite Hermitian matrix  $H_k = H_k^*$ . By splitting real and imaginary part, we write  $A_k = M_k + jN_k$  and  $H_k = P_k + j\Pi_k$ , where  $P_k = P_k^\top$  and  $\Pi_k = -\Pi_k^\top$  because  $H_k$  is Hermitian. Then,  $A_k^* H_k + H_k A_k + 2\alpha^* H_k = (M_k + jN_k)^*(P_k + j\Pi_k) + (P_k + j\Pi_k)(M_k + jN_k) + 2\alpha^*(P_k + j\Pi_k) = F + jG < 0$ , with  $F := M_k^\top P_k + P_k M_k + N_k^\top \Pi_k - \Pi_k N_k + 2\alpha^* P_k$  and  $G := M_k^\top \Pi_k + \Pi_k M_k - N_k^\top P_k + P_k N_k + 2\alpha^* \Pi_k$ . On the other hand, it can be checked, after some computations, that  $A_{e,k}^\top \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} + \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} A_{e,k} + 2\alpha^* \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} = \begin{bmatrix} F & G \\ -G & F \end{bmatrix}$ , which is negative definite, as to be proven, because  $\sigma\left(\begin{bmatrix} F & G \\ -G & F \end{bmatrix}\right) = \sigma(F + jG) \cup \sigma(F - jG)$ , as shown in the proof of (i)  $\iff$  (ii).

For the discrete-time case, in view of Lemma 4, Schur stability of  $\frac{1}{\alpha^*} A_k$  is equivalent to  $A_k^* H_k A_k - (\alpha^*)^2 H_k < 0$  for a positive definite Hermitian matrix  $H_k = H_k^*$ . By splitting real and imaginary part, we write  $A_k = M_k + jN_k$  and  $H_k = P_k + j\Pi_k$ , where  $P_k = P_k^\top$  and  $\Pi_k = -\Pi_k^\top$  because  $H_k$  is Hermitian. Then,  $A_k^* H_k A_k - (\alpha^*)^2 H_k = (M_k + jN_k)^*(P_k + j\Pi_k)(M_k + jN_k) - (\alpha^*)^2(P_k + j\Pi_k) = F + jG < 0$ , with  $F := M_k^\top P M + N_k^\top P N - M_k^\top \Pi_k M_k + N_k^\top \Pi_k M_k - (\alpha^*)^2 P_k$  and  $G := M_k^\top \Pi_k N_k - N_k^\top P M + M_k^\top \Pi_k M_k + N_k^\top \Pi_k N_k - (\alpha^*)^2 \Pi_k$ . On the other hand, it can be checked, after some computations, that  $A_{e,k}^\top \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} A_{e,k} - (\alpha^*)^2 \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} = \begin{bmatrix} F & G \\ -G & F \end{bmatrix}$ , which is negative definite, as to be proven, because  $\sigma\left(\begin{bmatrix} F & G \\ -G & F \end{bmatrix}\right) = \sigma(F + jG) \cup \sigma(F - jG)$ , as shown in the proof of (i)  $\iff$  (ii).

**Proof of (iii)  $\implies$  (iv).** According to Lemma 2, there exists an orthogonal matrix  $T \in \mathbb{R}^{N \times N}$  (satisfying  $T^\top T = I_N$ ) whose first column is  $\frac{1}{\sqrt{N}} \mathbf{1}_N$ , and such that  $\bar{L}_d = T^\top L_d T$  is as in (14). Let us now introduce the similarity transformation  $z = (T^\top \otimes I_n)x$ . Then, using the associative property of the Kronecker product, the dynamics in (4) can be rewritten as:

$$\dot{z}/z^+ = \bar{A}z := \left( (I_N \otimes A) - (\bar{L}_d \otimes BC) \right) z \quad (16)$$

where the upper block triangular structure of  $\bar{L}_d$  carries over to matrix  $\bar{A}$ , which can be written as

$$\bar{A} = \begin{bmatrix} A & A_{12} & \dots & A_{1\nu} \\ 0 & F_1 & \dots & A_{2\nu} \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & F_\nu \end{bmatrix} = \begin{bmatrix} A & M_0 \\ 0 & \bar{A}_1 \end{bmatrix} = \begin{bmatrix} A & M_0 \\ 0 & \begin{bmatrix} F_1 & M_1 \\ 0 & \bar{A}_2 \end{bmatrix} \end{bmatrix} = \begin{bmatrix} A & M_0 \\ 0 & \begin{bmatrix} F_1 & M_1 \\ 0 & \begin{bmatrix} F_2 & M_2 \\ 0 & \bar{A}_3 \end{bmatrix} \end{bmatrix} \end{bmatrix}, \quad (17)$$

and so on. In (17) we introduced the following notation:

$$\bar{A}_k := \begin{bmatrix} F_k & A_{k+1,k+2} & \dots & A_{k+1,\nu} \\ 0 & F_{k+1} & \dots & A_{k+2,\nu} \\ 0 & 0 & \ddots & \vdots \\ 0 & 0 & 0 & F_\nu \end{bmatrix},$$

$$M_{k-1} := \begin{bmatrix} A_{k,k+1} & \dots & A_{k,\nu} \end{bmatrix},$$



for  $k = 1, \dots, \nu$  with  $\bar{A}_\nu = F_\nu$ , and where the matrices in the diagonal blocks are induced by the structure of  $\bar{L}_d$  in (14). In particular, for each  $k = 1, \dots, \nu$ , if  $\lambda_k \in \mathbb{R}$ , then  $F_k \in \mathbb{R}^{n \times n}$  is given by  $F_k = A_k = A - \lambda_k BC$ . Then we may define  $\bar{P}_k := P_k$  and obtain,

$$F_k^\top \bar{P}_k + \bar{P}_k F_k \prec -2\alpha^* \bar{P}_k, \quad \text{if } \text{Im}(\lambda_k) = 0 \quad (18a)$$

$$\left( \text{resp. } F_k^\top \bar{P}_k F_k \prec (\alpha^*)^2 \bar{P}_k, \quad \text{if } \text{Im}(\lambda_k) \neq 0 \right). \quad (18b)$$

Instead, if  $\lambda_k \in \mathbb{C}$ , then  $F_k \in \mathbb{R}^{2n \times 2n}$  is given by  $F_k = (I_2 \otimes A) - (\Lambda_k \otimes BC)$ , with the spectrum of  $\Lambda_k$  being  $\sigma(\Lambda_k) = \{\lambda_k, \lambda_k^*\} = \{\alpha_k \pm j\beta_k\}$ , namely there exists an invertible  $S_k \in \mathbb{R}^{2 \times 2}$  such that  $\Lambda_k = S_k^{-1} \begin{bmatrix} \alpha_k & -\beta_k \\ \beta_k & \alpha_k \end{bmatrix} S_k$ . Now, since  $A_{e,k}$  in (9) can be expressed as

$$A_{e,k} = (I_2 \otimes A) - \left( \begin{bmatrix} \alpha_k & -\beta_k \\ \beta_k & \alpha_k \end{bmatrix} \otimes BC \right),$$

then  $F_k = (S_k^{-1} \otimes I_n) A_{e,k} (S_k \otimes I_n)$ . As a consequence, from item (iii), using matrices  $\begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix}$  and noting that  $\begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} = (I_2 \otimes P_k) + \left( \begin{bmatrix} 0 & -1 \\ 1 & 0 \end{bmatrix} \otimes \Pi_k \right)$ , we may construct  $\bar{P}_k := (S_k^\top \otimes I_n) \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} (S_k \otimes I_n) \succ 0$ , so that (11) transforms into

$$F_k^\top \bar{P}_k + \bar{P}_k F_k \prec -2\alpha^* \bar{P}_k, \quad \text{if } \text{Im}(\lambda_k) \neq 0 \quad (19a)$$

$$\left( \text{resp. } F_k^\top \bar{P}_k F_k \prec (\alpha^*)^2 \bar{P}_k, \quad \text{if } \text{Im}(\lambda_k) = 0 \right). \quad (19b)$$

Based on (18) and (19) and due to the block triangular structure of  $\bar{A}_1$ , there exist sufficiently small scalars  $\bar{\eta}_1, \dots, \bar{\eta}_{\nu-1}$  such that, defining  $\check{P} := \text{diag}(\bar{\eta}_1 \bar{P}_1, \dots, \bar{\eta}_{\nu-1} \bar{P}_{\nu-1}, \bar{P}_\nu)$  we have  $\bar{A}_1^\top \check{P} + \check{P} \bar{A}_1 \prec -2\alpha^* \check{P}$  (resp.  $\bar{A}_1^\top \check{P} \bar{A}_1 \prec (\alpha^*)^2 \check{P}$ ). Additionally, we can always say that there exists  $\alpha > \alpha^*$  (resp.  $0 < \alpha < \alpha^*$ ) such that  $\bar{A}_1^\top \check{P} + \check{P} \bar{A}_1 \leq -2\alpha \check{P}$  (resp.  $\bar{A}_1^\top \check{P} \bar{A}_1 \leq \alpha^2 \check{P}$ ). As a consequence, we may partition  $z = \begin{bmatrix} z_0 \\ \check{z} \end{bmatrix}$ , with  $z_0 \in \mathbb{R}^n$  and  $\check{z} \in \mathbb{R}^{(N-1)n}$  and define function  $W(z) := z^\top \bar{P} z := z^\top \text{diag}(0, \check{P}) z = \check{z}^\top \check{P} \check{z}$ , which satisfies, along the trajectories of system (16),

$$\dot{W}(z) = \check{z}^\top (\bar{A}_1^\top \check{P} + \check{P} \bar{A}_1) \check{z} \leq -2\alpha \check{z}^\top \check{P} \check{z} = -2\alpha W(z) \quad (20a)$$

$$\left( \text{resp. } W(z^+) = \check{z}^\top (\bar{A}_1^\top \check{P} \bar{A}_1) \check{z} \leq \alpha^2 \check{z}^\top \check{P} \check{z} = \alpha^2 W(z) \right). \quad (20b)$$

Based on (20), we define  $V(x) := W((T^\top \otimes I_n)x)$  satisfying (12a),(12b) (resp. (12a),(12c)), which immediately implies (12b) (resp. (12c)), because  $V$  corresponds to  $W$  in the equivalent coordinates  $x$ .

To prove (12a), let us first rewrite matrix  $\bar{P} := \text{diag}(0, \check{P})$  as follows, denoting by  $e_1$  the first element of the Euclidean basis, and introducing  $\hat{P} := (T \otimes I_n) \text{diag}(I_N, \check{P}) (T^\top \otimes I_n) \succ 0$ , we have

$$\begin{aligned} \bar{P} &= ((I_N - e_1 e_1^\top) \otimes I_n) \text{diag}(I_N, \check{P}) ((I_N - e_1 e_1^\top) \otimes I_n) \\ &= ((I_N - e_1 e_1^\top) T^\top \otimes I_n) \hat{P} (T(I_N - e_1 e_1^\top) \otimes I_n). \end{aligned} \quad (21)$$

Since the attractor  $\mathcal{A}$  in (5) is a linear subspace generated by vectors  $(\mathbf{1}_N \otimes I_n)$ , the distance  $|x|_{\mathcal{A}}$  can be characterized in terms of a suitable projection matrix  $\Psi$  as follows:

$$|x|_{\mathcal{A}} = |\Psi x| = \left| \left( \left( I_N - \frac{1}{N} \mathbf{1}_N \mathbf{1}_N^\top \right) \otimes I_n \right) x \right|, \quad (22)$$

where  $\Psi$  projects  $x$  in the directions that are orthogonal to the generator of  $\mathcal{A}$ .

Finally, using  $W(z) = z^\top \bar{P} z$ , the identity in (21), and noting that the orthogonality of  $T$  and its first column being  $\frac{1}{\sqrt{N}} \mathbf{1}_N$  implies  $T e_1 e_1^\top T^\top = \frac{1}{N} \mathbf{1}_N \mathbf{1}_N^\top$ , we may express  $V$  as

$$\begin{aligned} V(x) &= x^\top (T \otimes I_n) \bar{P} (T^\top \otimes I_n) x \\ &= x^\top \left( \left( I_N - \frac{1}{N} \mathbf{1}_N \mathbf{1}_N^\top \right) \otimes I_n \right) \hat{P} \left( \left( I_N - \frac{1}{N} \mathbf{1}_N \mathbf{1}_N^\top \right) \otimes I_n \right) x \\ &= x^\top \Psi^\top \hat{P} \Psi x, \end{aligned}$$

where  $\Psi$  is defined in (22). The positive definiteness of  $\hat{P}$  implies that  $c_1 I_{Nn} \preceq \hat{P} \preceq c_2 I_{Nn}$  for some positive scalars  $c_1, c_2$ , which in turn implies

$$c_1 |\Psi x|^2 \leq V(x) \leq c_2 |\Psi x|^2,$$

thus implying (12a) by virtue of (22).

**Proof of (iv)  $\implies$  (v).** For the continuous-time case, in view of the standard comparison lemma (Khalil, 2002, Lemma 3.4), condition (12b) implies the existence of a uniform negative exponential bound on  $V(x(t)) \leq e^{-2\alpha t} V(x(0))$ , along any solution  $x$ . This bound is easily extended to  $|x|_{\mathcal{A}}^2$  using (12a) in the following standard way:

$$|x(t)|_{\mathcal{A}}^2 \leq \frac{1}{c_1} V(x(t)) \leq \frac{e^{-2\alpha t}}{c_1} V(x(0)) \leq \frac{c_2}{c_1} e^{-2\alpha t} |x(0)|_{\mathcal{A}}^2.$$

For the discrete-time case, we can rewrite relation (12c) as  $V(x(t+1)) \leq \alpha^2 V(x(t))$ . Then, taking advantage of the chain relation between consecutive time instant, we can state that  $V(x(t)) \leq \alpha^{2t} V(x(0))$ . We can extend this bound to  $|x|_{\mathcal{A}}^2$  using (12a) in the following way:

$$|x(t)|_{\mathcal{A}}^2 \leq \frac{1}{c_1} V(x(t)) \leq \frac{\alpha^{2t}}{c_1} V(x(0)) \leq \frac{c_2}{c_1} \alpha^{2t} |x(0)|_{\mathcal{A}}^2.$$

**Proof of (v)  $\implies$  (vi).** From Lemma 1, a zero eigenvalue of  $L$  has non-negative left and right eigenvectors corresponding to  $p$  and  $\mathbf{1}_N$ . Non-negativity implies that the sum of the components of  $p$  cannot be zero (otherwise the components of  $p$  would all be zero and  $p$  would not be an admissible eigenvector). Hence,  $p^\top L = 0$  and  $p^\top \mathbf{1}_N \neq 0$ . Consider then the dynamics of the state  $\tilde{x}_o(t) := \frac{1}{p^\top \mathbf{1}_N} \sum_{k=1}^N p_k x_k(t)$  and note that from (1):

$$\dot{\tilde{x}}_o(t)/\tilde{x}_o^+(t) = A \frac{1}{p^\top \mathbf{1}_N} \sum_{k=1}^N p_k x_k(t) + B \frac{1}{p^\top \mathbf{1}_N} \sum_{k=1}^N p_k u_k(t) = A \tilde{x}_o(t) - B \frac{1}{p^\top \mathbf{1}_N} p^\top L y = A \tilde{x}_o(t).$$

Then  $\tilde{x}_o$  evolves autonomously following (13), and corresponds to a linear combination of states  $x_k$  weighted by the (non-negative) components of the eigenvector  $p$ . Uniform global  $\alpha$ -exponential stability of the attractor  $\mathcal{A}$  implies that all states  $x_k$  converge globally and exponentially to a common trajectory  $\bar{x}$  with convergence rate at least  $\alpha$ , i.e.  $\lim_{t \rightarrow +\infty} x_k(t) - \bar{x}(t) = 0$  and  $|x_k(t) - \bar{x}(t)| \leq M e^{-\alpha t} |x_k(0) - \bar{x}(0)|$  (resp.  $|x_k(t) - \bar{x}(t)| \leq M \alpha^t |x_k(0) - \bar{x}(0)|$ ) for all  $k$ . This common trajectory asymptotically coincides with the solution to the initial value problem (13), because, using  $p^\top \mathbf{1}_N = \sum_{k=1}^N p_k$ , we obtain

$$\lim_{t \rightarrow +\infty} \tilde{x}_o(t) - \bar{x}(t) = \lim_{t \rightarrow +\infty} \frac{1}{p^\top \mathbf{1}_N} \sum_{k=1}^N p_k x_k(t) - \frac{\sum_{k=1}^N p_k}{p^\top \mathbf{1}_N} \bar{x}(t) = \frac{1}{p^\top \mathbf{1}_N} \sum_{k=1}^N p_k \lim_{t \rightarrow +\infty} (x_k(t) - \bar{x}(t)) = 0.$$

**Proof of (vi)  $\implies$  (ii).** We prove this step by contradiction. Therefore, we will prove that given a matrix  $A_{e,k} + \alpha^* I$  not Hurwitz (resp. a matrix  $\frac{1}{\alpha^*} A_{e,k}$  not Schur), the sub-states  $x_i$  do not uniformly globally  $\alpha^*$ -exponentially synchronize. In other words, we do not have synchronization to the unique solution of the following problem:

$$\dot{\tilde{x}}_o = (A + \alpha^* I) \tilde{x}_o \tag{23a}$$

$$\left( \text{resp. } \tilde{x}_o^+ = \frac{1}{\alpha^*} A \tilde{x}_o \right). \tag{23b}$$

Assume that one of the matrices  $A_{e,k}$  in (9) has spectral abscissa greater than  $-\alpha^*$  (resp. spectral radius grater than  $\alpha^*$ ), and assume without loss of generality that it is  $A_{e,\nu}$ . Consider the coordinate system in (16) with (17). Then, from the upper block triangular structure of  $\bar{A}$  in (17), we obtain that  $\bar{A}_\nu + \alpha^* I$  is not Hurwitz (resp.  $\frac{1}{\alpha^*} \bar{A}_\nu$

not Schur) ( $\bar{A}_v = F_v$ ), and then there exists a vector  $\omega^* \in \mathbb{R}^n$  (an eigenvector of one of the non-converging natural modes) such that the solution to  $\dot{z} = (\bar{A} + \alpha^* I)z$  (resp.  $z^+ = \frac{1}{\alpha^*} \bar{A}z$ ) starting at  $z^*(0) = [\mathbf{0}_n^\top \ \dots \ \mathbf{0}_n^\top \ \omega^{*\top}]^\top$  corresponds to  $z^*(t) = [\mathbf{0}_n^\top \ \dots \ \mathbf{0}_n^\top \ z_v^{*\top}(t)]^\top$ , where  $z_v^*(t)$  does not converge to zero. Define now a function  $z \mapsto W(z) = \tilde{z}^\top I_{N(n-1)} \tilde{z}$  as specified before (20) (that is, the same function  $W$  for the specific selection  $\tilde{P} = I_{N(n-1)}$ ). Evaluating  $W$  along solutions, we get that  $W(z) = |z_v^*(t)|^2$  does not converge to zero. With  $x \mapsto V(x)$  defined after (20), we have that (12a) holds, and evaluating  $V$  along the solution  $x^*(t) = (T \otimes I_n)z^*(t)$ , we have that  $V$  does not converge to zero, which implies that  $x^*$  does not converge to the consensus set  $\mathcal{A}$ . In other words, the components of  $x^*(t)$  do not synchronize to the solution of (23) as to be proven.

#### 4. Conclusions

We have provided necessary and sufficient conditions for the synchronization of identical linear SISO systems, both in the continuous-time and in the discrete-time case, which do not require any assumption on the graph (whose topology is just assumed to be time-invariant). Our conditions provide a guaranteed rate of convergence to the synchronization set and apply also to systems where a direct input-to-output channel is present.

#### Acknowledgements

The authors thank Laura Dal Col for her contribution to a preliminary version of this paper, and Dimos Dimarogonas and Elena Panteley for useful discussions.

#### References

- Adhikari, B., Morărescu, I.C., Panteley, E., 2021. An emerging dynamics approach for synchronization of linear heterogeneous agents interconnected over switching topologies. *IEEE Control Systems Letters* 5, 43–48.
- Agaev, R., Chebotarev, P., 2005. On the spectra of nonsymmetric Laplacian matrices. *Linear Algebra and its Applications* 399, 157–168.
- Anderson, B.D.O., Ye, M., 2019. Recent Advances in the Modelling and Analysis of Opinion Dynamics on Influence Networks. *International Journal of Automation and Computing* 16, 129–149.
- Andrieu, V., Jayawardhana, B., Tarbouriech, S., 2018. Some Results on Exponential Synchronization of Nonlinear Systems. *IEEE Transactions on Automatic Control* 63, 1213–1219.
- Bernstein, D.S., 2005. *Matrix Mathematics: Theory, Facts, and Formulas with Application to Linear Systems Theory*. Princeton University Press.
- Bonacich, P., 1987. Power and centrality: a family of measures. *American Journal of Sociology* 5, 1170–1182.
- Carli, R., Chiuso, A., Schenato, L., Zampieri, S., 2011. Optimal Synchronization for Networks of Noisy Double Integrators. *IEEE Transactions on Automatic Control* 56, 1146–1152.
- Caughman, J.S., Veerman, J.J.P., 2006. Kernels of directed graph Laplacians. *The Electronic Journal of Combinatorics* 13, R39.
- Cristofaro, A., Mattioni, M., 2022. Multiconsensus control of homogeneous LTI hybrid systems under time-driven jumps, in: *2022 IEEE 61st Conference on Decision and Control (CDC)*, pp. 316–321.
- Dal Col, L., 2016. *On Distributed Control Analysis and Design for Multi-Agent Systems Subject to Limited Information*. Ph.D. thesis. INSA de Toulouse.
- Dal Col, L., Queinnee, I., Tarbouriech, S., Zaccarian, L., 2019. Regional  $H_\infty$  Synchronization of Identical Linear Multiagent Systems Under Input Saturation. *IEEE Transactions on Control of Network Systems*.
- Dal Col, L., Tarbouriech, S., Zaccarian, L., 2018.  $H_\infty$  control design for synchronisation of identical linear multi-agent systems. *International Journal of Control* 91, 2214–2229.
- Dal Col, L., Tarbouriech, S., Zaccarian, L., Kieffer, M., 2017. A consensus approach to PI gains tuning for quality-fair video delivery. *International Journal of Robust and Nonlinear Control* 27, 1547–1565.
- Dörfler, F., Chertkov, M., Bullo, F., 2013. Synchronization in complex oscillator networks and smart grids. *Proceedings of the National Academy of Sciences* 110, 2005–2010.
- Fagnani, F., Frasca, P., 2017. *Introduction to Averaging Dynamics over Networks*. Springer Berlin Heidelberg, New York, NY.
- Fax, J., Murray, R., 2004. Information flow and cooperative control of vehicle formations. *IEEE Transactions on Automatic Control* 49, 1465–1476.
- Hale, J.K., 1997. Diffusive coupling, dissipation, and synchronization. *Journal of Dynamics and Differential Equations* 9, 1–52.
- Hara, S., Tanaka, H., Iwasaki, T., 2014. Stability Analysis of Systems With Generalized Frequency Variables. *IEEE Transactions on Automatic Control* 59, 313–326.
- Horn, R.A., Johnson, C.R., 2012. *Matrix Analysis*. 2nd ed., Cambridge University Press, Cambridge ; New York.
- Isidori, A., 2017. *Lectures in Feedback Design for Multivariable Systems*. Advanced Textbooks in Control and Signal Processing, Springer International Publishing, Cham.

- Jadbabaie, A., Lin, J., Morse, A., 2003. Coordination of groups of mobile autonomous agents using nearest neighbor rules. *IEEE Transactions on Automatic Control* 48, 988–1001.
- Khalil, H., 2002. *Nonlinear Systems*. 3rd ed., Prentice Hall, USA.
- Khong, S.Z., Lovisari, E., Rantzer, A., 2016. A Unifying Framework for Robust Synchronization of Heterogeneous Networks via Integral Quadratic Constraints. *IEEE Transactions on Automatic Control* 61, 1297–1309.
- Luenberger, D.G., 1979. *Introduction to Dynamic Systems: Theory, Models and Applications*. John Wiley & Sons.
- Mayhew, C.G., Sanfelice, R.G., Sheng, J., Arcak, M., Teel, A.R., 2012. Quaternion-Based Hybrid Feedback for Robust Global Attitude Synchronization. *IEEE Transactions on Automatic Control* 57, 2122–2127. doi:10.1109/TAC.2011.2180777.
- Moreau, L., 2005. Stability of multiagent systems with time-dependent communication links. *IEEE Transactions on Automatic Control* 50, 169–182.
- Olfati-Saber, R., Fax, J.A., Murray, R.M., 2007. Consensus and Cooperation in Networked Multi-Agent Systems. *Proceedings of the IEEE* 95, 215–233.
- Olfati-Saber, R., Murray, R., 2004. Consensus problems in networks of agents with switching topology and time-delays. *IEEE Transactions on Automatic Control* 49, 1520–1533.
- Panteley, E., Loria, A., 2017. Synchronization and dynamic consensus of heterogeneous networked systems. *IEEE Transactions on Automatic Control* 62, 3758–3773.
- Pecora, L.M., Carroll, T.L., 1998. Master stability functions for synchronized coupled systems. *Phys. Rev. Lett.* 80, 2109–2112. doi:10.1103/PhysRevLett.80.2109.
- Ren, W., Beard, R., 2008. Consensus algorithms for double-integrator dynamics. *Distributed Consensus in Multi-vehicle Cooperative Control: Theory and Applications*, 77–104.
- Ren, W., Beard, R.W., Atkins, E.M., 2007. Information consensus in multivehicle cooperative control. *IEEE Control Systems Magazine* 27, 71–82. doi:10.1109/MCS.2007.338264.
- Saberi, A., Stoorvogel, A.A., Zhang, M., Sannuti, P., 2022. *Synchronization of Multi-Agent Systems in the Presence of Disturbances and Delays. Systems & Control: Foundations & Applications*, Springer International Publishing, Cham.
- Scardovi, L., Arcak, M., Sontag, E.D., 2010. Synchronization of Interconnected Systems With Applications to Biochemical Networks: An Input-Output Approach. *IEEE Transactions on Automatic Control* 55, 1367–1379.
- Scardovi, L., Sepulchre, R., 2009. Synchronization in networks of identical linear systems. *Automatica* 45, 2557–2562.
- Seo, J.H., Shim, H., Back, J., 2009. Consensus of high-order linear systems using dynamic output feedback compensator: Low gain approach. *Automatica* 45, 2659–2664.
- Sepulchre, R., 2011. Consensus on nonlinear spaces. *Annual Reviews in Control* 35, 56–64.
- Slotine, J.J.E., Wang, W., 2005. A Study of Synchronization and Group Cooperation Using Partial Contraction Theory, in: Kumar, V., Leonard, N., Morse, A.S. (Eds.), *Cooperative Control: A Post-Workshop Volume 2003 Block Island Workshop on Cooperative Control*. Springer, Berlin, Heidelberg. *Lecture Notes in Control and Information Science*, pp. 207–228.
- Stykel, T., 2002. Stability and inertia theorems for generalized Lyapunov equations. *Linear Algebra and its Applications* 355, 297–314.
- Su, Y., Huang, J., 2012. Two consensus problems for discrete-time multi-agent systems with switching network topology. *Automatica* 48, 1988–1997.
- Teel, A.R., Poveda, J.I., 2015. A hybrid systems approach to global synchronization and coordination of multi-agent sampled-data systems. *IFAC-PapersOnLine* 48, 123–128. doi:10.1016/j.ifacol.2015.11.163.
- Wieland, P., Kim, J.S., Scheu, H., Allgöwer, F., 2008. On consensus in multi-agent systems with linear high-order agents. *IFAC Proceedings Volumes* 41, 1541–1546.
- Wieland, P., Sepulchre, R., Allgöwer, F., 2011. An internal model principle is necessary and sufficient for linear output synchronization. *Automatica* 47, 1068–1074.
- Wimmer, H.K., 1973. On the Ostrowski-Schneider inertia theorem. *Journal of Mathematical Analysis and Applications* 41, 164–169.
- Xia, T., Scardovi, L., 2014. Synchronization conditions for diffusively coupled linear systems, in: *21st International Symposium on Mathematical Theory of Networks and Systems*, pp. 1070–1075.
- Xiao, F., Wang, L., 2007. Consensus problems for high-dimensional multi-agent systems. *IET Control Theory & Applications* 1, 830–837.
- Zaupa, N., Zaccarian, L., Tarbouriech, S., Queinnec, I., Giordano, G., 2023. Controlling identical linear multi-agent systems over directed graphs, in: *2023 IEEE 62st Conference on Decision and Control (CDC)*, pp. –. URL: <https://laas.hal.science/hal-04357943>.
- Zhu, L., Chen, Z., Middleton, R.H., 2016. A General Framework for Robust Output Synchronization of Heterogeneous Nonlinear Networked Systems. *IEEE Transactions on Automatic Control* 61, 2092–2107.