



Equivalent Conditions for the Synchronization of Identical Linear Systems

Nicola Zaupa, Giulia Giordano, Isabelle Queinnec, Sophie Tarbouriech, Luca Zaccarian

► To cite this version:

Nicola Zaupa, Giulia Giordano, Isabelle Queinnec, Sophie Tarbouriech, Luca Zaccarian. Equivalent Conditions for the Synchronization of Identical Linear Systems. Workshop "Methods and Algorithms for the Control of Complex Systems", Aug 2024, Banyuls sur-mer, France, France. 2024. hal-04700228

HAL Id: hal-04700228

<https://laas.hal.science/hal-04700228v1>

Submitted on 17 Sep 2024

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.




Distributed under a Creative Commons Attribution - NonCommercial - NoDerivatives 4.0 International License

Motivation

Several conditions for linear systems synchronization have been proposed along the years. We show their equivalence as necessary and sufficient conditions for uniform global exponential synchronization of N identical single-input-single-output (SISO) systems, connected through a directed graph (without any assumption). Both the **continuous-time** and the **discrete-time** case are considered.

Problem formulation



Let us consider N identical SISO dynamical systems of arbitrary order, with state $x_i \in \mathbb{R}^n$ evolving as

$$\begin{aligned}\dot{x}_i / x_i^+ &= Ax_i + Bu_i \\ y_i &= Cx_i + du_i\end{aligned}\quad i = 1, \dots, N \quad (1)$$

and with scalar inputs $u_i \in \mathbb{R}$ and outputs $y_i \in \mathbb{R}$, interconnected through a directed graph \mathcal{G} with Laplacian $L \in \mathbb{R}^{N \times N}$ as follows:

$$u = -Ly = -L((I_N \otimes C)x + du), \quad (2)$$

where $u = [u_1 \dots u_N]^\top \in \mathbb{R}^N$, $y = [y_1 \dots y_N]^\top \in \mathbb{R}^N$ and $x := [x_1^\top \dots x_N^\top]^\top \in \mathbb{R}^{Nn}$.

For the sake of generality, we also allow for the presence of a direct input-output link $d \in \mathbb{R}$ in (1). With $d \neq 0$, the implicit equation (2) can be uniquely solved as

$$u = -(L_d \otimes C)x := -((I_N + dL)^{-1}L \otimes C)x \quad (3)$$

if and only if matrix $I_N + dL$ is invertible, i.e., $-d^{-1}$ is not an eigenvalue of L . When $d = 0$, we retrieve the classical case $L_d := L$. Overall, the linear distributed interconnection (1), (2) can be written as

$$\dot{x} / x^+ = (I_N \otimes A)x - (L_d \otimes BC)x. \quad (4)$$

The synchronization set, or **attractor**, is defined as

$$\mathcal{A} := \{x : x_i - x_j = 0, \forall i, j \in \{1, \dots, N\}\}. \quad (5)$$

Definitions

(α -UGES) For $\alpha > 0$ there exist $M > 0$ such that

$$|x(t)|_{\mathcal{A}} \leq M e^{-\alpha t} |x(0)|_{\mathcal{A}}, \quad \forall t \in \mathbb{R}_{\geq 0}$$

$$(\text{resp. } |x(t)|_{\mathcal{A}} \leq M \alpha^t |x(0)|_{\mathcal{A}}, \quad \forall t \in \mathbb{N}).$$

(α -synchronization) Every i -th sub-system satisfies

$$|x_i(t) - \tilde{x}_o(t)| \leq M e^{-\alpha t} \sum_{i=1}^N |x_i(0) - \tilde{x}_o(0)|, \quad \forall t \in \mathbb{R}_{\geq 0}$$

$$(\text{resp. } |x_i(t) - \tilde{x}_o(t)| \leq M \alpha^t \sum_{i=1}^N |x_i(0) - \tilde{x}_o(0)|, \quad \forall t \in \mathbb{N}),$$

$i = 1, \dots, N$, for a suitable target trajectory \tilde{x}_o .

Synchronization conditions

Before stating the main result, we note that, trivially, all the zero eigenvalues of L are also zero eigenvalues of $L_d = (I_N + dL)^{-1}L$. Then we denote by $0 = \lambda_0, \lambda_1, \dots, \lambda_\nu$ the eigenvalues of L_d , where the complex conjugate pairs are only counted once (so that $\nu := N - 1 - n_c$, with n_c being the number of complex conjugate pairs).

Consider the **continuous-time** (resp. **discrete-time**) system in (1), (2), the attractor \mathcal{A} in (5) and the parameter $\alpha^* \geq 0$ (resp. $\alpha^* \in (0, 1]$). The following statements are equivalent:

- [Complex condition] The **spectral abscissa** (resp. **spectral radius**) of the complex-valued matrices

$$A_k := A - \lambda_k BC, \quad k = 1, \dots, \nu, \quad (6)$$

is smaller than $-\alpha^*$ (resp. α^*).

- [Real condition] The **spectral abscissa** (resp. **spectral radius**) of the real-valued matrices

$$A_{e,k} := \begin{bmatrix} A - \operatorname{Re}(\lambda_k)BC & \operatorname{Im}(\lambda_k)BC \\ -\operatorname{Im}(\lambda_k)BC & A - \operatorname{Re}(\lambda_k)BC \end{bmatrix}, \quad k = 1, \dots, \nu, \quad (7)$$

is smaller than $-\alpha^*$ (resp. α^*).

- [Lyapunov inequality] For each $k = 1, \dots, \nu$, there exist real-valued matrices $P_k = P_k^\top \succ 0$ and $\Pi_k^\top = -\Pi_k$ such that one of the following identities holds:

$$(P_k + j\Pi_k)A_k + A_k^*(P_k + j\Pi_k) \prec -2\alpha^*(P_k + j\Pi_k) \quad (8a)$$

$$(\text{resp. } A_k^*(P_k + j\Pi_k)A_k \prec (\alpha^*)^2(P_k + j\Pi_k)), \quad (8b)$$

or

$$\begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} A_{e,k} + A_{e,k}^\top \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} \prec -2\alpha^* \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} \quad (9a)$$

$$(\text{resp. } A_{e,k}^\top \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix} A_{e,k} \prec (\alpha^*)^2 \begin{bmatrix} P_k & \Pi_k \\ -\Pi_k & P_k \end{bmatrix}). \quad (9b)$$

- [Lyapunov function] There exist $\alpha > \alpha^*$ (resp. $0 < \alpha < \alpha^*$), positive constants c_1, c_2 and c_3 , and a strict quadratic Lyapunov function $V(x)$ satisfying:

$$c_1 |x|_{\mathcal{A}}^2 \leq V(x) \leq c_2 |x|_{\mathcal{A}}^2, \quad (10a)$$

$$\dot{V}(x) \leq -2\alpha V(x) \quad (10b)$$

$$(\text{resp. } V(x^+) \leq \alpha^2 V(x)). \quad (10c)$$

- [UGES] There exists $\alpha > \alpha^*$ (resp. $0 < \alpha < \alpha^*$) such that the closed attractor \mathcal{A} in (5) is α -UGES for the closed loop (1), (2).

- [IVP] There exists $\alpha > \alpha^*$ (resp. $0 < \alpha < \alpha^*$) such that, for the closed loop (1), (2), the sub-states x_i uniformly globally α -exponentially synchronize to the unique solution of the following initial value problem:

$$\dot{\tilde{x}}_o / \tilde{x}_o^+ = A\tilde{x}_o, \quad \tilde{x}_o(0) = \frac{1}{p^\top \mathbf{1}_N} \sum_{k=1}^N p_k x_k(0), \quad (11)$$

where $p := [p_1 \dots p_N]^\top \in \mathbb{R}^N$ is a left eigenvector corresponding to the zero eigenvalue of L .

References

[1]



Equivalent Conditions for the Synchronization of Identical Linear Systems over Arbitrary Interconnections
Nicola Zaupa, Giulia Giordano, Isabelle Queinnec, Sophie Tarbouriech, Luca Zaccarian
European Journal of Control, 2024